

---

**EASY SOUND<sup>®</sup>**  
**EM55000S Series**

**Tiny Controller-Based Speech  
Synthesizer with PWM Output**

**Product  
Specification**

**Doc. VERSION 1.2**

**ELAN MICROELECTRONICS CORP.**

January 2005

---



**Trademark Acknowledgments:**

**IBM is a registered trademark and PS/2 is a trademark of IBM.**

**Windows is a trademark of Microsoft Corporation.**

**ELAN and ELAN logo  are trademarks of ELAN Microelectronics Corporation.**

Copyright © 2005 by ELAN Microelectronics Corporation

**All Rights Reserved**

Printed in Taiwan

The contents of this specification are subject to change without further notice. ELAN Microelectronics assumes no responsibility concerning the accuracy, adequacy, or completeness of this specification. ELAN Microelectronics makes no commitment to update, or to keep current the information and material contained in this specification. Such information and material may change to conform to each confirmed order.

In no event shall ELAN Microelectronics be made responsible for any claims attributed to errors, omissions, or other inaccuracies in the information or material contained in this specification. ELAN Microelectronics shall not be liable for direct, indirect, special incidental, or consequential damages arising from the use of such information or material.

The software (if any) described in this specification is furnished under a license or nondisclosure agreement, and may be used or copied only in accordance with the terms of such agreement.

ELAN Microelectronics products are not intended for use in life support appliances, devices, or systems. Use of ELAN Microelectronics product in such applications is not supported and is prohibited.

**NO PART OF THIS SPECIFICATION MAY BE REPRODUCED OR TRANSMITTED IN ANY FORM OR BY ANY MEANS WITHOUT THE EXPRESSED WRITTEN PERMISSION OF ELAN MICROELECTRONICS.**



**ELAN MICROELECTRONICS CORPORATION**

**Headquarters:**

No. 12, Innovation Road 1  
Hsinchu Science Park  
Hsinchu, Taiwan 308  
Tel: +886 3 563-9977  
Fax: +886 3 563-9966  
<http://www.emc.com.tw>

**Hong Kong:**

**Elan (HK) Microelectronics Corporation, Ltd.**  
Rm. 1005B, 10/F Empire Centre  
68 Mody Road, Tsimshatsui  
Kowloon, HONG KONG  
Tel: +852 2723-3376  
Fax: +852 2723-7780  
[elanhk@emc.com.hk](mailto:elanhk@emc.com.hk)

**USA:**

**Elan Information Technology Group**  
1821 Saratoga Ave., Suite 250  
Saratoga, CA 95070  
USA  
Tel: +1 408 366-8223  
Fax: +1 408 366-8220

**Europe:**

**Elan Microelectronics Corp. (Europe)**

Siewerdtstrasse 105  
8050 Zurich, SWITZERLAND  
Tel: +41 43 299-4060  
Fax: +41 43 299-4079  
<http://www.elan-europe.com>

**Shenzhen:**

**Elan Microelectronics Shenzhen, Ltd.**

SSMEC Bldg., 3F, Gaoxin S. Ave.  
Shenzhen Hi-Tech Industrial Park  
Shenzhen, Guangdong, CHINA  
Tel: +86 755 2601-0565  
Fax: +86 755 2601-0500

**Shanghai:**

**Elan Microelectronics Shanghai Corporation, Ltd.**

23/Bldg. #115 Lane 572, Bibo Road  
Zhangjiang Hi-Tech Park  
Shanghai, CHINA  
Tel: +86 021 5080-3866  
Fax: +86 021 5080-4600

# Contents

<b>1</b>	<b>General Description .....</b>	<b>1</b>
<b>2</b>	<b>Features .....</b>	<b>1</b>
<b>3</b>	<b>Pin Descriptions .....</b>	<b>2</b>
<b>4</b>	<b>Absolute Maximum Ratings .....</b>	<b>2</b>
<b>5</b>	<b>Electrical Characteristics .....</b>	<b>3</b>
<b>6</b>	<b>Application Circuit .....</b>	<b>3</b>
6.1	Heavy Noise for Motor Application Circuit .....	4



### Specification Revision History

Doc. Version	Revision Description	Date
1.0	Initial version	2002/03/27
1.1	Added Application Circuits	2003/01/28
1.2	Revised RAM size from 32 nibbles to 48 nibbles for EM55007S & EM55009S; and 64 nibbles for EM55012S & EM550015S	2005/01/11



## 1 General Description

EM55000S series is a series of 3 to 15 seconds single chip high quality voice synthesizer IC. It is based on a tiny controller and is very suitable for low cost high quality toy market application.

## 2 Features

- 3 to 15 seconds voice capacity
- 5-bit ASPCM speech synthesis
- Port 2 provides wake-up function
- Power down mode for energy saving
- One 6 bit timer overflow control is provided
- 38KHz modulation for IR transmission
- Two stacks for subroutine call
- Direct Drive PWM output for voice
- Sample rate (KHz) : 4.3 / 5 / 6 / 7.5 / 10 / 15

Product	EM55003S	EM55005S	EM55007S	EM55009S	EM55012S	EM55015S
Duration (@ 6k sample rate)	3 sec	5 sec	7 sec	9 sec	12 sec	15 sec
ROM (bits)	10Kx10	16Kx10	28Kx10	32Kx10	44Kx10	48Kx10
PROG. ROM (bits)	8Kx10	16Kx10				
RAM (nibbles)	32		48		64	
I/O pins	2 I/O	4 I/O			6 I/O	
	P2.0, P2.1	P2.0, P2.1, P3.2, P3.3			P2.0, P2.1, P2.2, P3.1, P3.2, P3.3	
IR	No	Yes				
Voice silence compression	No	Yes				
Flash with Volume (pin)	Yes (P2.1)	Yes (P3.3)				



### 3 Pin Descriptions

Symbol	I/O	Function
P2.0	I/O	Bit 0 of Port 2
P2.1	I/O	Bit 1 of Port 2
P2.2	I/O	Bit 2 of Port 2 (excluding EM55003S ~ EM55009S)
P3.1	I/O	Bit 2 of Port 3 (excluding EM55003S ~ EM55015S)
P3.2	I/O	Bit 2 of Port 3 (exluding EM55003S)
P3.3	I/O	Bit 3 of Port 3 (exluding EM55003S)
VDD	I	Positive digital power supply.
OSCI	I	Ring oscillator input pin.
VSSD	I	Negative digital power supply.
VCC	I	Positive analog power supply
VSSC	I	Negative analog power supply
VO1	O	PWM output 1
VO2	O	PWM output 2

### 4 Absolute Maximum Ratings

Items	Symbol	Min	Max	Unit
Supply Voltage	VDD-VSS	-0.3	+6.0	V
Input Voltage	VIN	VSS-0.3	VDD+0.3	V
Operating Temperature	TOP	-20.0	+70.0	0C
Storage Temperature	TSTG	-55.0	+125.0	0C



## 5 Electrical Characteristics

(25°C, Vdd=3.0 Volts unless otherwise specified)

Items	Sym	Min.	Typ.	Max.	Unit	Condition
Operating Voltage	VDD	2.2	3.0	5.5	V	-
Standby Current	IDDS	-	-	2.0	uA	VDD=3V
Operating Current	IDDO	-	250	350	uA	VDD=3V, no load, PWM D/A stop
P2, P3 Drive Current	IOD	2.0	3.0	4.5	mA	VDD=3V, VO=2.4V
P2 Sink Current	IOS	-	3.0	10.0	uA	VDD=3V
P3 Sink Current	IOS	2.3	3.5	4.5	mA	VDD=3V, VO=0.4V
VO1, VO Output Current	IVO	150	180	-	mA	VDD=3V, Vo1=Vo2=1.5 V
Oscillation Resistor	R	-	220	-	KΩ	VDD=3V
Oscillation Freq.	FOSC	1.75	1.92	2.1	MHz	VDD=3V

## 6 Application Circuit

Applicable notes to the following application circuits:

1. For noisy power supply application, suppress noise by adding ceramic capacitor between VCC and ground near the IC's VDD pad. The recommended capacitor value is 0.1μF.
2. For heavy loading application, it is recommended that an electrolytic capacitor is added between VCC and ground. The recommended capacitor value for button cell applications is 10μF.
3. The recommended value for button cell internal impedance is 750Ω or less.
4. The use of spring direct trigger is not recommended. If you must use such trigger, you need to add a ceramic capacitor between trigger pin and ground to debounce the spring noise. The recommend capacitor value is 0.001 ~ 0.01 μF.

## 6.1 Heavy Noise for Motor Application Circuit

